

# Pramac P2000i Silent Petrol Generator

**Prod Code: 5000-PRAM2-608**

2.kW 230v Yamaha Powered Petrol Inverter Generator

## P-SERIES

Pramac's inverter range delivers the right type of power to supply equipment that is sensitive to voltage surges. Power inverters change direct current (DC) from a battery to alternating current (AC) power that is used by a range of electric devices and equipment, including lights, power tools, computers, and more. These connect to a battery and an AC device, providing users with portable power.

## SPECIFICATIONS

Engine	Yamaha MZ80
Displacement	79cc
Socket Configuration	1 x 13A
Max Output	2kW (2.5kVA)
Continuous Output	1.6kW (2kVA)
Noise Level @ 7M	59dB(a)
Recoil Start	Yes
Electric Start	No
Fuel Tank Capacity	4.2L
Run Time at 75% Load	0.79 L/H
Weight (Kg)	22
Length (cm)	49.8
width (cm)	28.9
Height (cm)	46.1
Additional Options	LPG Dual Fuel Conversion - Hours Meter

