

Honda EG4500 4.5KW Digital AVR Petrol Generator

Prod Code: 5000-HOND2-59

The new EG4500 delivers a maximum output of 4.5kW for the demanding professional, combining superb durability and value, with the power stability required for today's equipment. For tasks such as powering tools and incandescent lamps simultaneously, the new Digital AVR delivers smoother power with greatly reduced risk of light flicker or damage to sensitive electronics. Simple yet rugged design features also make the EG4500 easy to use, with centralised controls and outlets, full tubular frame and a large fuel tank to give 9 hours of continuous running time at half load.

SPECIFICATIONS

Fuel type	Unleaded petrol
Primary usage	Professional Use
Type	Open Frame
Max output (W)	4500
Output voltage (V)	115/230V
Rated output (W)	4000
Frequency rating (Hz)	50
DC voltage	N/A
Power Stability	Digital AVR Output®
DC current	N/A
Engine type	GX390
Type	single cylinder 4-stroke OHV air cooled
Oil capacity	1.1 litre with Oil Alert®
Starter system	recoil
Length (mm)	681
Width (mm)	530
Height (mm)	570
Dry weight (kg)	79
Noise Level (1/4 load) (dB(a)*)	85
Run Time at Rated Load	9h30min
Fuel tank capacity (litres)	24
Petrol Consumption	2.52L/H
Options	LPG Dual Fuel Conversion -Wheel Kit



EG4500 / EG5500

EG4500CL, EG5500CL: BT type

