

GCE6000H 6.5kW (8kVA) Elec Start Honda GX390 Petrol Generator

Prod Code: 5000-GEAR1-19273

Designed and manufactured in the UK by GearGB

SPECIFICATIONS

Engine	Honda GX390
Fuel	Petrol
Alternator	Meccalte S16F single phase
Voltage	115v / 230v
Socket Outlets	1x16A 1x32A 115v / 1x16A 1x32A 230v
Max Power Output	6.5kW (8kVA @0.8pf)
Continuous Power Output	5.5kW (6.9kVA @0.8pf)
Recoil Start	Yes
Key Operated Electric Start	Yes
Wheel Kit C/W Fold Down Handles	Yes
Lifting Eye	Yes
Noise Level @ 7M	70dB(a)
Noise Level LWA	96LW(a)
Weight	108kg
Fuel Tank Capacity	6.2L
Petrol Consumption @75%	2.2 L/H
Options	115/230v - 230v only - 115v only - Side Facing 1x32A 230V Socket - AVR - LPG Dual Fuel Conversion - LPG Bottle Holder - Long Run 20L Petrol Tank

