

GCE10500HT 13kVA (10.5kW) 3 Phase Honda GX630 Generator

Prod Code: 5000-GEAR1-19861

3 Phase 3000RPM portable generator powered by Honda V-twin air cooled GX630 engine.

Designed and manufactured in the UK by GearGB.

SPECIFICATIONS

Engine	Honda GX630
Engine Warranty	3 Years
Fuel	Petrol
Alternator	Meccalte T20F 3 Phase
Max Output	10.5kW (13kVA @0.8pf)
Rated Output	9.1kW (11.4kVA @0.8pf)
Voltage	230v / 415v
Socket Configuration	1x16A 230v + 1x32A 415v
Key Operated Electric Start	Yes
Recoil Start	No
RCD Protection	Yes
Engine Mounting	Low Vibration Angle Mounts
Noise Level @ 7M	71dB(a)
Noise Level LWA	96LW(a)
Fuel Tank Capacity	20L
Petrol Consumption	@Rated 6.2L/H @75% 5.4L/H @50% 4.1L/H @25% 2.9L/H
Oil Alert Shutdown	Yes
Oil Capacity	1.9L
Lifting Eye	Included
Wheel Kit C/W Fold Down Handles	Included
Weight (Kg)	155
Additional Options	LPG Dual Fuel Conversion - LPG Only Conversion
Alternative Options	Pneumatic Wheels - AVR

