

GCL8000BT 3-Phase 8kW (10kVA) Briggs & Stratton Petrol Generator

Prod Code: 5000-GEAR1-20646

Designed and manufactured in the UK by GearGB

*image shows optional wheel kit

SPECIFICATIONS	
Engine	Briggs & Stratton XR2100
Fuel	Petrol
Alternator	Meccalte T20F three phase
Voltage	415v / 230v
Socket Outlets	1x32A 415v / 1x16A 230v
Max Power Output	8kW (10kVA @0.8pf)
Continuous Power Output	6.2kW (7.8kVA @0.8pf)
Recoil Start	Yes
Electric Start	No
Noise Level @ 7M	70dB(a)
Noise Level LWA	96LW(a)
Weight	93kg
Fuel Tank Capacity	6.6L
Petrol Consumption @75%	2.4 L/H
Options	Wheel Kit - AVR - LPG conversion

