

AVR GCL3200H 2.9kW (3.6kVA) 230v Honda GX200 Petrol Generator

Prod Code: 5000-GEAR1-22023

Designed and manufactured in the UK by GearGB

SPECIFICATIONS

Engine	Honda GX200
Engine Warranty	3 Years
Fuel	Petrol
Alternator	Meccalte ES16W
AVR	Yes
Max Output	2.9kW (3.6kVA)
Rated Output	2.6kW (3.38kVA)
Voltage	230v
230v Socket Configuration	1x16A (side mount socket)
Frame	Powder Coated
Key Operated Electric Start	No
Recoil Start	Yes
Engine Mounting	Low Vibration Angle Mounts
Noise Level @ 7M	70dB(a)
Noise Level LWA	95LW(a)
Fuel Tank Capacity	3.3L
Consumption @75% Load	1.1(L/H)
Oil Alert Shutdown	Yes
Oil Capacity	0.6L
RPM	3000
Cylinder	1
Cooling	Air
Weight (Kg)	42
Length (cm)	59.5
width (cm)	41
Height (cm)	43
Additional Options	LPG Dual Fuel Conversion

