

GCE8000BT VANGUARD 8kW (10kVA) Elec Start Petrol 3-Phase Generator

Prod Code: 5000-GEAR1-24352

VANGUARD engines are the premium range by Briggs & Stratton. Advantages include;

- **EASIER STARTING** with new optimised starting design
- **LOWER MAINTENANCE** with cyclonic air filter (up to 600 hour replacement interval) and advanced oil management system, increasing oil life by up to 50% (up to 200 hour replacement interval)
- **ENHANCED PROTECTION** with Vanguards 'TransportGuard' eliminates oil/fuel dilution problem and offers 3-in-1 control lever
- **USER COMFORT** with Lower noise and Less vibration
- **UP TO 4 YEAR ENGINE WARRANTY** with 3 year standard warranty and additional 1 year warranty for registering your engine with Vanguard warranty online https://www.vanguardpower.com/eu/en_gb/support/engine-registration.html

Designed and manufactured in the UK by GearGB

*Image shows optional wheel kit

SPECIFICATIONS

Engine	Vanguard 14HP
Fuel	Petrol
Alternator	Meccalte T20F Three phase
Voltage	415v / 230v
Socket Outlets	1x32A 415v / 1x16A 230v
Max Power Output	8kW (10kVA @0.8pf)
Continuous Power Output	6.2kW (7.8kVA @0.8pf)
Recoil Start	Yes
Key Operated Electric Start	Yes
Wheel Kit C/W Fold Down Handles	Yes
Lifting Eye	Yes
Noise Level @ 7M	70dB(a)
Noise Level LWA	96LW(a)
Weight	119kg
Fuel Tank Capacity	6.6L
Petrol Consumption @75%	2.4 L/H
Options	AVR - LPG Dual Fuel Conversion - LPG Bottle Holder - Long Run 20L Petrol Tank

