

Pramac E6900 Recoil Start 110v / 230v GX390 Petrol Generator

Prod Code: 5000-PRAM1-21174

6.4kW Dual Voltage Honda Powered Petrol Site Generator

E-SERIES

Open frame light compact generators with a basic configuration and very easy to transport: the best balance between price and performance.

The Pramac E6900 is a petrol generator designed specifically for intensive operations where performance and power is demanded by professional users over an extended period of time. Housed within a heavy duty tubular steel frame and powered by the well proven petrol Honda GX390 13hp 4 stroke engine.

SPECIFICATIONS

Engine	Honda GX390
HP	13
Max Output	6.4kW (8kVA)
Noise Level @ 7M	69dB(a)
Guaranteed noise level (LWA)	97dB(A)
Recoil Start	Yes
Electric Start	No
Fuel Tank Capacity	6.2L
Run Time at 75% Load	3.04H
Weight (Kg)	75
Length (cm)	71.5
width (cm)	55
Height (cm)	54.5
Socket Configuration	2x115v 16A 1x115v 32A / 2x230v 16A
Additional Options	Wheel Kit - LPG Dual Fuel Conversion - Hours Meter

