

Pramac S8000 Electric Start 230V / 110V Long Run

Prod Code: 5000-PRAM1-760

S-SERIES

Think of the right attributes for the power your activity demands. The S Series offers reliability and performance, for the most demanding applications.

The Pramac S8000 has all the features of a top class generator: a powerful and economical engine, a strong and modern design and a long-run easy filling fuel tank.

A quiet and compact electric start machine fitted with the well proven Honda petrol GX390 13hp 4 stroke engine.

SPECIFICATIONS

Standby kVA (LTP)	7.2
Standby KW (LTP)	6.4
Prime kVA (COP)	6
Prime KW (COP)	5.5
Frequency	50hz
Voltage	230/115V
Phase	Single
Engine Make	Honda
Engine Model	GX390
Fuel	Petrol
Start Type	Recoil Start
Fuel Tank Capacity	26.5 Litres
Run Time @ 75% Load	12.38Hours
Fuel consumption @ 75%	2.14 L/H
Noise Level	69db(A) @ 7m
Noise Level LWA	97db(A)
Dimmensions (LWH)	840mm x 615mm x 753mm
Dry Weight	109kg
Socket Configeration	2 x 230v 16A 1 x 115v 16A 1 x 115v 32A

