

Sincro EA200AC 200AMP AC Welder Generator Alternator (j609b)

Prod Code: 5010-SINC-WA200

Sincro 2-Pole AC Brushless Welder Generator Alternator.

Direct replacement alternator for EW200 AC

- Protection: IP23
- Weldable electrodes: Rutile
- Supplied with autoresettable thermal breaker against overload
- Can also be used as single phase alternator

This unit is designed to be fitted to an engine of 13hp or above with a 7/8 inch taper shaft (j609b coupling). Check the attached technical drawing 'Taper Shaft Drawings' to match against your existing coupling. If a different coupling is required, please contact us for availability.

Petrol eg. Honda GX390 / Briggs & Stratton XR2100 series

Diesel eg. Yanmar L100 / Lombardini 15LD 440 / Hatz 1B40

SPECIFICATIONS

Model	EA200 AC
Type	EA 2L
Weld Current (Amps)	200AC
Weld Voltage	55
Duty Cycle	60% @ 180Amps
Duty Cycle	35% @ 200Amps
110v output (Kw)	3.5
230v output (Kw)	7
RPM	3000
Weight (Kg)	42
Dimensions inc Sockets (L x W x H)	49 x 22 x 34cm
Taper Fitting	7/8" (j609b)



forma costruttiva / shape IM B35 - j609b cod.D/F

Spz - Type	Dimensione / Dimension	
	Ø	Ø
	(mm)	(mm)
EA / ED 2 H	377.5	283
EA / ED 2 L	432.5	338

Spz - Type	Dimensione / Dimension	
	Ø	Ø
	(mm)	(mm)
EA / ED 2 H	22.14	22.14
EA / ED 2 L	25.4	25.4

