

WLE200AH 200AMP AC Elec Start Honda Welder Generator

Prod Code: 7000-GEAR-19265

Portable welder generator powered by Honda GX390

Designed and manufactured in the UK by GearGB

SPECIFICATIONS

Engine	Honda GX390
Engine Warranty	3 Years
Fuel	Petrol
Alternator	Sincro EA200 AC
Weld Current (amps)	200 AC
Weld voltage (OCV)	55v
Duty Cycle 200A	35%
Duty Cycle 160A	60%
Welding Socket Configuration	2 x DINS 10-25mm
Aux Socket Configuration	1x16A 230v 1x16A 115V
230V Output	4kW (5kVA)
110V Output	2.2kW (2.75kVA)
Recoil Start	Yes
Key Operated Electric Start	Yes
Wheel Kit C/W Fold Down Handles	Yes
Lifting Eye	Yes
Welding Tray Dimensions (cm)	L31 W33 H12
Engine Mounting	Low Vibration Angle Mounts
Noise Level @ 7M	72dB(a)
Noise Level LWA	96LW(a)
Standard Fuel Tank Capacity	6.2L
Petrol Consumption @75% Load	2.2(L/H)
Oil Alert Shutdown	Yes
Oil Capacity	1.1L
RPM	3000
Cylinder	1
Cooling	Air
Weight (Kg)	119
Additional Options	Welding Cables - LPG Dual Fuel Conversion - LPG Bottle Holder - Long Run 20L Petrol Tank

