GCE12000H 12kW (15kVA) Honda GX690 Petrol Generator

Prod Code: 5000-GEAR1-19124

Single phase 3000RPM portable generator powered by Honda V-twin air cooled GX690 engine. Designed and manufactured in the UK by GearGB.

| CDECIEICATIONS | |
|------------------------------------|--|
| SPECIFICATIONS | |
| Engine | Honda GX690 |
| Engine Warranty | 3 Years |
| Fuel | Petrol |
| Alternator | Meccalte S20F Single Phase |
| Max Output | 12kW (15kVA @0.8pf) |
| Rated Output | 11kW (13.75kVA @0.8pf) |
| Voltage | 230v OR 230v/115v |
| Socket Configuration | (2x16A + 1x32A) 230v |
| Key Operated Electric Start | Yes |
| Recoil Start | No |
| Overload Protection | MCB + Socket Trips |
| Engine Mounting | Low Vibration Angle Mounts |
| Noise Level @ 7M | 70dB(a) |
| Noise Level LWA | 96LW(a) |
| Fuel Tank Capacity | 20L |
| Petrol Consumption (L/H) | @Rated 6.2 @75% 6 @50% 4.1 @25%2.9 |
| Oil Alert Shutdown | Yes |
| Oil Capacity | 1.9L |
| Lifting Eye | Included |
| Wheel kit C/W fold down handles | Included |
| Wheel Type | Pneumatic |
| Weight (Kg) | 155 |
| Additional Options | LPG Dual Fuel Conversion - Generator Control Module |
| Alternative Options | 230v 1x(63A) socket - 115v / 230v Dual Voltage (1x16A + 1x32A 230v / 1x16A +1x32A 115v)- RCD - LPG Conversion - AVR - Hard Wheels |



