

LPG DUAL FUEL GCL5000BT 3-Phase 5kW (6kVA) Briggs & Stratton Generator

Prod Code: 5000-GEAR1-22072

Designed and manufactured in the UK by GearGB

* Image shows optional wheel kit

SPECIFICATIONS

Engine	Briggs & Stratton XR1450 Series
Fuel	LPG / Petrol
Alternator	Meccalte T16F three phase
Voltage	415v / 230v
Socket Outlets	1x32A 415v / 1x16A 230v
Max Power Output	5kW (6kVA @0.8pf)
Continuous Power Output	4.5kW (5.6kVA @0.8pf)
Recoil Start	Yes
Electric Start	No
Noise Level @ 7M	70dB(a)
Noise Level LWA	96LW(a)
Weight	67kg
Fuel Tank Capacity	5.3L
Petrol Consumption @75%	1.8 L/H
LPG Consumption @75%	1.2KG/H
Options	Wheel Kit - AVR - LPG conversion

