

iGCE8000H 8kW (10kVA) Elec Start Honda iGX390 Petrol Generator

Prod Code: 5000-GEAR1-23394

Designed and manufactured in the UK by GearGB

SPECIFICATIONS

Engine	Honda iGX390 Auto-Choke Engine
Fuel	Petrol
Alternator	Meccalte S20F single phase
Voltage	115v / 230v
Socket Outlets	1x16A 1x32A 115v / 1x16A 1x32A 230v
Max Power Output	8kW (10kVA @0.8pf)
Continuous Power Output	6.2kW (7.7kVA @0.8pf)
Recoil Start	Yes
Key Operated Electric Start	Yes
Wheel Kit C/W Fold Down Handles	Yes
Lifting Eye	Yes
Noise Level @ 7M	70dB(a)
Noise Level LWA	95LW(a)
Weight	119kg
Fuel Tank Capacity	6.2L
Petrol Consumption @75%	2.4 L/H
Options	115/230v - 230v only - 115v only - Side Facing 1x32A 230V Socket - AVR - LPG Dual Fuel Conversion - LPG Bottle Holder - Long Run 20L Petrol Tank

