

# VEHICLE MOUNT LPG DUAL FUEL GCE6000H 6.5kW (8kVA) ELEC START Honda Generator

**Prod Code: 5000-GEAR1-23856**

LPG / Petrol dual fuel generator. Fitted with thermostat overtemperature shutdown

Designed and manufactured in the UK by GearGB

## SPECIFICATIONS

Engine	Honda GX390
Fuel	Petrol / LPG Propane
Alternator	Meccalte S16F single phase
Voltage	230v Only
Socket Outlets	1x32A
Max Power Output	6.5kW (8kVA @0.8pf)
Continuous Power Output	5.5kW (6.9kVA @0.8pf)
Recoil Start	Yes
Key Operated Electric Start	Yes
Wheel Kit C/W Fold Down Handles	Yes
Lifting Eye	Yes
Noise Level @ 7M	70dB(a)
Noise Level LWA	96LW(a)
Weight	88kg
Fuel Tank Capacity	6.2L
Petrol Consumption @75%	2.2 L/H
LPG Consumption @75%	1.8KG/H
L x W x H (mm)	775 x 505 x 505
Options	AVR - Solenoid operated LPG kit

