

LPG DUAL FUEL GCL3000H 2.8kW (3.4kVA) 110v/230v Honda GX200 Petrol Generator

Prod Code: 5000-GEAR1-24394

Designed and manufactured in the UK by GearGB

SPECIFICATIONS

Engine	Honda GX200
Engine Warranty	3 Years
Fuel	LPG Propane or Petrol
Alternator	Meccalte S15W
AVR	No
Max Output	2.8kW (3.4kVA)
Rated Output	2.6kW (3.38kVA)
Voltage	110v / 230v
230v Socket Configuration	1x16A
110v Socket Configuration	1x16A
Frame	Powder Coated
Key Operated Electric Start	No
Recoil Start	Yes
Engine Mounting	Low Vibration Angle Mounts
Noise Level @ 7M	70dB(a)
Noise Level LWA	95LW(a)
Fuel Tank Capacity	3.3L
Petrol Consumption @75% Load	1.1(L/H)
LPG Consumption @75% Load	0.9(KG/H)
Oil Alert Shutdown	Yes
Oil Capacity	0.6L
RPM	3000
Cylinder	1
Cooling	Air
Weight (Kg)	40
Length (cm)	59.5
width (cm)	41
Height (cm)	43
Alternative Options	110v only - 230v only - Schuko 230v

