

Sincro EW130AC 130AMP AC Welder Generator Alternator (j609a)

Prod Code: 5010-SINC-WA130

Sincro 2-Pole AC Brushless Welder Generator Alternator

This unit is designed to be fitted to an engine of up to 7 HP with a 3/4 inch taper shaft (j609a). This unit can also be run via a belt a pulley with a bearing kit.

- Protection: IP23
- Weldable electrodes: Rutile
- Supplied with autoresettable thermal breaker against overload
- Can also be used as single phase alternator

SPECIFICATIONS

Weld Current (Amps)	130AC
Weld Voltage	55
Duty Cycle	35% @ 130Amps
110v output (Kw)	3
230v output (Kw)	3
RPM	3000
Weight (Kg)	32
Dimensions inc Sockets (L x W x H)	41 x 19 x 34cm
Taper Fitting	3/4" (j609a)
Capacitor size	35UF



V-type

