

# WL200DH PRO 200AMP DC Honda Welder Generator

**Prod Code: 7000-GEAR-19126**

Portable welder generator powered by Honda GX390. Features British manufactured 100% duty cycle @ 200A welding alternator

Designed and manufactured in the UK by GearGB

## SPECIFICATIONS

Engine	Honda GX390
Engine Warranty	3 Years
Fuel	Petrol
Alternator	GB 200DC
Weld Current (amps)	200 DC
Weld voltage (V)	90
Duty Cycle 200A	80%
Duty Cycle 160A	100%
Welding Socket Configuration	2 x DINS 35-50mm
Variable Current Control	Yes
Aux Socket Configuration	1x16A 230v 1x16A 110V
230V Output	2.5kW (3kVA)
110V Output	2.5kW (3kVA)
Welding Tray	Yes
Recoil Start	Yes
Engine Mounting	Low Vibration Angle Mounts
Noise Level @ 7M	72dB(a)
Noise Level LWA	96LW(a)
Fuel Tank Capacity	6.2L
Petrol Consumption @75% Load	2.2(L/H)
Oil Alert Shutdown	Yes
Oil Capacity	1.1L
RPM	3000
Cylinder	1
Cooling	Air
Weight (Kg)	99
Additional Options	Welding Cables - Wheel Kit - LPG Dual Fuel Conversion

